

D07 Cover Plates

| | |
|--|--|
| <p>Circuit -"XXXX"</p> <p>Optional gauge port G</p> <p>UNC mounting kit Includes: 4 - 3/8"-16 x 1.50" SHCS 2 - 1/4"-20 x 1.50" SHCS 4 - 118 O-ring viton 2 - 111 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> <p>Metric mounting kit includes: 4 - M10-1.5 x 40mm SHCS 2 - M6-1.0 x 40mm SHCS 4 - 118 O-ring viton 2 - 111 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> | <p>Circuit -"PABT"</p> <p>Optional gauge port G</p> <p>UNC mounting kit Includes: 4 - 3/8"-16 x 2.50" SHCS 2 - 1/4"-20 x 2.50" SHCS 2 - 118 O-ring viton 2 - 111 O-ring viton 1 - 136 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> <p>Metric mounting kit includes: 4 - M10-1.5 x 60mm SHCS 2 - M6-1.0 x 60mm SHCS 2 - 118 O-ring viton 2 - 111 O-ring viton 1 - 136 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> |
| <p>Circuit -"PBAT"</p> <p>Optional gauge port G</p> <p>UNC mounting kit includes: 4 - 3/8"-16 x 2" SHCS 2 - 1/4"-20 x 2" SHCS 2 - 136 O-ring viton 2 - 111 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> <p>Metric mounting kit includes: 4 - M10-1.5 x 50mm SHCS 2 - M6-1.0 x 50mm SHCS 2 - 136 O-ring viton 2 - 111 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> | <p>Circuit -"PTXX"</p> <p>Optional gauge port G</p> <p>UNC mounting kit includes: 4 - 3/8"-16 x 1.50" SHCS 2 - 1/4"-20 x 1.50" SHCS 2 - 118 O-ring viton 2 - 111 O-ring viton 1 - 132 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> <p>Metric mounting kit includes: 4 - M10-1.5 x 40mm SHCS 2 - M6-1.0 x 40mm SHCS 2 - 118 O-ring viton 2 - 111 O-ring viton 1 - 132 O-ring viton 2 - pin 1 - Plug (with gauge option)</p> |

PART NUMBER SYSTEM

D07 Aluminum Cover Plate with All Ports Blocked & No Gauge Port Example : **CPA07GXXXXAAXU**

| TYPE | MATERIAL | VALVE PATTERN | CIRCUIT CODE | GAUGE PORT CODE | LOCATION OF GAUGE PORTS | MOUNTING | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
|-------------------|---------------------------------------|--|--|-----------------|-------------------------|----------|-------------------|------|---------------------------------------|------|---------------------------------------|------|------------------|---|------|------|------|----|------|------|----|-----|---|----|------|------|----|------|------|----|------|------|----|--------|-----|---|---|------|---|--------|---|---|---|---|--------------------------|---|---------------------------------|
| CP Cover Plate | A Aluminum D Ductile Iron | 07G ISO 4401-07-06 NFPA T3.5.1-D07 | <table border="1"> <thead> <tr> <th>CODE</th> <th>CIRCUIT</th> </tr> </thead> <tbody> <tr> <td>XXXX</td> <td>All Ports Blocked</td> </tr> <tr> <td>PABT</td> <td>P Connected to A, B Connected to T</td> </tr> <tr> <td>PBAT</td> <td>P Connected to B, A Connected to T</td> </tr> <tr> <td>PTXX</td> <td>P Connected to T</td> </tr> </tbody> </table> | CODE | CIRCUIT | XXXX | All Ports Blocked | PABT | P Connected to A, B Connected to T | PBAT | P Connected to B, A Connected to T | PTXX | P Connected to T | <table border="1"> <thead> <tr> <th>CODE</th> <th>TYPE</th> <th>SIZE</th> </tr> </thead> <tbody> <tr> <td>AA</td> <td>None</td> <td>None</td> </tr> <tr> <td>SC</td> <td>SAE</td> <td>6</td> </tr> <tr> <td>NB</td> <td>NPTF</td> <td>1/4"</td> </tr> <tr> <td>BB</td> <td>BSPP</td> <td>1/4"</td> </tr> <tr> <td>TB</td> <td>BSPT</td> <td>1/4"</td> </tr> <tr> <td>MB</td> <td>Metric</td> <td>M10</td> </tr> </tbody> </table> | CODE | TYPE | SIZE | AA | None | None | SC | SAE | 6 | NB | NPTF | 1/4" | BB | BSPP | 1/4" | TB | BSPT | 1/4" | MB | Metric | M10 | <table border="1"> <thead> <tr> <th>X</th> <th>None</th> </tr> </thead> <tbody> <tr> <td>P</td> <td>P Port</td> </tr> </tbody> </table> | X | None | P | P Port | <table border="1"> <thead> <tr> <th>U</th> <th>M</th> </tr> </thead> <tbody> <tr> <td>U</td> <td>UNC Std for SAE & NPT</td> </tr> <tr> <td>M</td> <td>Metric Std for BSP* & Metric</td> </tr> </tbody> </table> | U | M | U | UNC Std for SAE & NPT | M | Metric Std for BSP* & Metric |
| CODE | CIRCUIT | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| XXXX | All Ports Blocked | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PABT | P Connected to A, B Connected to T | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PBAT | P Connected to B, A Connected to T | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| PTXX | P Connected to T | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| CODE | TYPE | SIZE | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| AA | None | None | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| SC | SAE | 6 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| NB | NPTF | 1/4" | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| BB | BSPP | 1/4" | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| TB | BSPT | 1/4" | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| MB | Metric | M10 | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| X | None | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| P | P Port | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| U | M | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| U | UNC Std for SAE & NPT | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |
| M | Metric Std for BSP* & Metric | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | | |

WE RESERVE THE RIGHT TO DISCONTINUE MODELS, OR CHANGE SPECIFICATIONS WITHOUT NOTICE OR INCURRING OBLIGATION

Lynch Products Can Be Modified to Suit Your Application